




**NR1403**  
SLIM DESIGN AV RECEIVER



As a five-channel slim-line AV Receiver, the NR1403 also offers a host of connectivity options. Fans of devices such as camcorders and a variety of smartphones or tablets will love the front panel HDMI input for easy and instant video / music enjoyment. The 5x 50W output can be used for a simple stereo set-up but is also powerful enough to run a full 5.1 system, creating spectacular surround sound and converting your living room into a sensational cinema. You will also be pleased about the easy set-up - with the help of the Setup Assistant, Audyssey MultEQ and Microphone there is no need to study the manual, just follow the on-screen instructions. In addition, the NR1403 has separate on-board decoders for both standard and high-definition audio such as DTS-HD and Dolby TrueHD, while its total of six HDMI inputs handle a multitude of digital sources, so you can easily hook-up your satellite box, BD/DVD player, game console and camcorder... all at the same time. All with just one HDMI cable connected to your screen. It all adds up to fabulous sound, great video quality and elegant slim-line appearance.



**Main Features**

- Dolby TrueHD and dts-HD Master Audio
- 5x 50 Watts at 8 ohm RMS
- Dynamic Volume and Dynamic EQ
- Pure Direct
- HDMI: 5+1 in / 1out (3D, ARC, Deep Color)
- M-DAX2 - audio expander for compressed music
- M-Xport for Bluetooth with optional RX101



**EAN**

<b>EU</b>	NR1403/N1B	4951035047521	Black
	NR1403/N1SG	4951035047538	Silver-Gold
<b>UK</b>	NR1403/T1B	4951035047521	Black
	NR1403/T1SG	4951035047538	Silver-Gold

## NR1403

### SLIM DESIGN AV RECEIVER



FEATURES	NR1403
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	0 / 0 / 0 / 0
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX	0 / 0 / 0
Multichannel Stereo	0
Compressed audio Enhancer: MDAX2	0
<b>OTHERS</b>	
Bluetooth audio via RX101	optional
Auto speaker setup by microphone	Audyssey MultEQ
Audyssey Dynamic EQ / Dynamic Volume	0 / 0
HDMI path though on stand-by	0
3D video pass through	0
Audio Return Channel	0
On Screen Display: GUI	0
GUI overlay on HDMI	0
Setup Wizard (ENG, GER, FR)	0
Variable cross over	0
<b>INPUTS/OUTPUTS</b>	
<b>VIDEO</b>	
Composite In / Out	3 / 1
HDMI In / Out (version x.x)	5+1 / 1 (1.4)
<b>AUDIO</b>	
Analogue In / Out	4 / 0
Digital Optical In / Out	1 / 0
Digital Coaxial In / Out	1 / 0
Multichannel Pre Out	0 (2.1)
Subwoofer Out	1
Headphone Out	1

<b>OTHER</b>	
M-XPort for RX101	0
Marantz remote bus	0
Front HDMI Input	0
<b>SPECIFICATIONS</b>	
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)	80 W
Audio Signal to Noise Ratio	98 dB
AM/FM Tuner	0
<b>GENERAL</b>	
Available colors: Black / Silver-Gold	0 / 0
System Remote Control	RC018SR
Power Consumption in W	180
Standby Consumption in W	0.2 W (Standby) / 0.5 W (CEC standby)
Maximum Dimensions (W x D x H) in mm	440 x 367 x 105
Weight in kg	8.3

Design and specifications are subject to change by Marantz without notice.