



marantz®

Product information

SR5006 AV RECEIVER



The SR5006 also features the famous Marantz circular display, and it has the same networking facilities as his big brother for audio streaming, Internet radio, and AirPlay from any iDevice. It also includes decoders for standard audio as well as for Dolby TrueHD and DTS-HD Master Audio. And, it comes with no less than six HDMI 1.4 inputs – making it immediately ready for 3D video and ARC (Audio Return Channel) from ARC-compatible TV sets. It easily handles the most demanding of scenes in action films, as well as offering excellent-quality music playback, thanks to the latest Marantz audio technologies. To ensure you get the best possible audio with compressed files from iPod via USB, the SR5006 offers 7x 100W rms and incorporates the M-DAX2 – Marantz Dynamic Expander version2. This neat little addition also optimises the quality of MP3 files from either CD or the optional Bluetooth Receiver RX101. Everything sounds clearer, more detailed, and more alive. To finish off, the SR5006 comes with a whole range of convenience features such as: Setup Wizard, the “auto calibration” with Audyssey MultiEQ and Dynamic Volume Control; “Multi-Room” with multi-source flexibility; “video-off” mode to ensure you enjoy your music and your movies in true dynamic Marantz style. It also has the specially developed Marantz Wizz App for bi-directional control via any iDevice. All of which makes the SR5006 a true combination of style, power and ease.

Main Features

- 7x 100 Watts 8 ohms RMS
- DLNA1.5 Network audio streaming and Internet radio
- AirPlay installed
- Audyssey MultEQ XT, Dynamic EQ and Dynamic Volume
- 6in / 1out HDMI 1.4 (3D/ARC/CEC)
- iPod / iPhone compatible USB input
- Transparent GUI multilingual Setup Wizard
- Multi room/Multi source
- Learnable Remote Control

EAN

EU	SR5006/N1B	4951035044551
	SR5006/N1SG	4951035044568
UK	SR5006/T1B	4951035044797
	SR5006/T1SG	4951035044803

because music matters



marantz®

SR5006 AV RECEIVER



FEATURES	SR5006
MULTICHANNEL SURROUND	
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	0 / 0 / 0 / 0
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	0 / 0 / 0 / 0
Audyssey DSX	-
Multichannel Stereo	0
Dolby Headphone	-
Compressed audio Enhancer: MDAX / MDAX2	- / 0
SOUND ENHANCEMENTS	
Current Feedback Topology	-
Hyper Dynamic Amplifier Modules (HDAM)	-
High Grade Audio Components	-
NETWORK	
DLNA Certified	0 (v1.5)
Network Audio: MP3 / WAV / AAC / FLAC / FLAC 96/24 / WMA	0 / 0 / 0 / 0 / 0 / 0
Internet Radio: direct / external media player	0 / 0
vTuner / Napster* / last.fm*	0 / 0 / 0
Ethernet	0
OTHERS	
Bluetooth audio via RX101	optional
Auto speaker setup by microphone	Audyssey MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume	0 / 0
Video conversion	CVBS > HDMI; Comp > HDMI
Analogue to HDMI scaling	-
HDMI to HDMI scaling	-
Videoprocessing	0
Picture adjust / Noise reduction	- / -
HDMI path though on stand-by	0
3D video pass through	0
Audio Return Channel	0
On Screen Display: GUI / OSD	0 / -
GUI overlay on HDMI	0
Setup Wizard (ENG, GER, FR)	0
Variable cross over	0
Multiroom zones	1

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	4 / 1
Component In / Out	2 / 1
HDMI In / Out (version x.x)	6 / 1 (1.4)
Multi-Room Video Out: Video / Component	- / -
AUDIO	
Analogue In / Out	6 / 1
Phono (MM) In	-
Digital Optical In / Out	2 / 0
Digital Coaxial In / Out	2 / 0
Multichannel Pre Out / Main In	0 (2.2) / -
Subwoofer Out	2
7.1 multichannel input	0
OTHER	
M-XPort for RX101	0
Speaker A / B	0
Height speaker terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting) / Speaker C	0 / 0
Multi-Room Speaker Terminal	0
Marantz remote bus	0
IR Flasher In	0
Network: (IP-control / update)	0 / 0
RS232C (control / update)	0 / 0
DC Triggers	-
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	0 / 0 / - / - / 0
USB Audio / Made for iPod / Works with iPhone	0 / 0 / 0
SPECIFICATIONS	
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)	100 W
70% Guarantee	0
Audio Signal to Noise Ratio	100 dB
FM Tuner	0
GENERAL	
Available colors: Gold / Silver / Black / Silver-Gold	- / - / 0 / 0
Metal Front Panel	-
System Remote Control	RC014SR
Pre-programmed / Learnable / LCD Display	0 / 0 / -
Power Consumption in W	650
Standby Consumption in W	0.2
Maximum Dimensions (W x D x H) in mm	440 x 389 x 161
Weight in kg	10.6

* Not available in all regions

Design and specifications are subject to change by Marantz without notice.

because music matters

www.marantz.eu